

Spectre simulations for APTS SF and APTS with in-pixel amplifier

Andrei Dorokhov
09/06/22

Simulation: description and parameters

4 combinations of pixels are simulated AC/DC and with/without in-pixel amplifier:









- 1) DCpix_ampl
- 2) ACpix_ampl
- 3) DCpix
- 4) ACpix

- Signal varied from 10 to 1640e
- ENC calculated for 100e, where all pixels are in linear range
- Some biasing parameters optimized for in-pixel amplifier circuit
- Detector diode emulated with capacitance $c_{det}=2\text{fF}$, leakage 2fA
- AC coupling capa 5fF
- PCB load capacitance 5pF




	Name	Value
1	IRESET	100n
2	IBIASP	20u
3	IBIASN	1.6m
4	IBIAS3	400u
5	IBIAS4	6m
6	VRESET	200m
7	PWELL	0
8	calib_capa	160a
9	cdet	2f
10	ileak	2f
11	in_coupling_capa	6f
12	Cpcb	5p
13	Qin	100

Signal transient response



Feuille de calcul
Microsoft Excel

Noise spectra and ENC



pixel	ENC
DCpix_ampl	15.4 e
ACpix_ampl	19.2 e
DCpix	27.9 e
ACpix	32.9 e



Feuille de calcul
Microsoft Excel